

# P4500 230V 50HZ #CONN #DPP

## THE SILENT POWER



Low noise level, it is the ideal generator for use in residential areas or outside normal working hours. It's equipped with a reliable Diesel engine, first class components and complete instrumentation.

### Main Features

Frequency	Hz	50
Voltage	V	230
Power factor	cos $\phi$	0.9
Phase and connection		1

### Power Rating

Standby power LTP	kVA	4.1
Standby power LTP	kW	3.7
Continuous power COP	kVA	3.5
Continuous power COP	kW	3.1

#### Ratings definition (According to standard ISO8528 1:2005)

**COP** - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

**LTP** - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

### Engine specifications

Engine manufacturer		Yanmar
Model		L70N
Engine cooling system		Air
Displacement	cm <sup>3</sup>	320
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Diesel
Oil capacity	l	1.1
Starting system		Electric



### Alternator Specifications

Class		H
IP protection		23
Poles		2
Frequency	Hz	50
Voltage regulation system		Capacitor

### Dimensional data

Length	(L) mm	800
Width	(W) mm	520
Height	(H) mm	690
Dry weight	Kg	99
Fuel tank capacity	l	18

### Autonomy

Fuel consumption @ 75% PRP	l/h	1.15
Fuel consumption @ 100% PRP	l/h	1.24
Running time @ 75% PRP	h	15.65
Running time @ 100% PRP	h	14.52

### Noise level

Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 7 mt	dB(A)	68

## GENSET CONTROL PANELS (CONN DPP)



Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.

### COMMANDS

- Start selector switch with key: OFF - ON - START
- **CONN**ector for AMF/RSS (Accessory available)

### INSTRUMENTATION

- Voltmeter

### PROTECTIONS

- Circuit breaker
- Cover protection circuit breaker IP55
- Differential protection (**DPP**)
- Low Oil Pressure

### SOCKET TYPE

SCHUKO 230V 16A IP54	1
2P+T CEE 230V 16A IP44	1
2P+T CEE 230V 32A IP44	1

## ACCESSORIES CONTROL PANEL

### AMF - AUTOMATIC CONTROL PANEL (CONN)

This accessory permits to control all the functions about a generator. It's built to monitor mono phase or three phase with neutral systems in alternate current; it permits to transfer the user's load on generator when the mains voltage is faulty. Conversely, as soon as AMF system detects the power grid, it stops the generator.

#### Equipment:

- Control and protection unit (DGT)
- Phase detector
- Contactor with interblock
- Battery charged
- Acoustic alarm
- 8 meters control wiring (with CONNector)
- External start stop capability
- Emergency stop button

#### Instrumentation (DGT):

- Mains voltage
- Genset voltage
- Frequency meter
- Hour meter

#### Alarm & Shutdowns:

- Generators voltage out of limits
- Battery Voltage out of limits
- Low oil Pressure
- Fail to start
- External shutdown



### RSS - REMOTE START / STOP (CONN)

RSS Remote start/stop wireless with CONNector (max Distance 90m)



## ACCESSORIES

### TRANSPORTATION KIT

- With fix handles
- With folding handles



### LIGHT TOWER

for portable generators (with tubular frames)

- Maximum Height 4.2m
- Elevations Pneumatic
- Quick open/close systems for legs
- Mast support and four lifting
- Lamp available Watt/Type:
  - n.4 X 500W Halogen (required power from generator: 2.5kVA 230V Single Phase)
  - n.4 X 1000W Halogen (required power from generator: 5,0kVA 230V Single Phase)



### MTS- MANUAL TRANSFER SWITCH

- Manual transfer switch 40A (for manual control versions 230V)

